

PCMINI - MINIATURE PHOTOCELL KIT**Description:**

5A Photovoltaic switch used for street light, gardens, gates entrance lights, show windows, shops and sign boards and illuminations.



PCMINI

OTHER ADDITIONAL INFORMATION**Electrical Connection:**

For incandescent lamp, connect black wire and white (common) to power source, Red wire and White to lamp load.

Caution:

The control unit may be damaged by disconnecting.

All Models:

Turn ON at approximately 10-30Lux
Turn OFF at approximately 100-150Lux

Mounting hole diameter:

17mm

- Save energy by turning ON/OFF the lights at dusk and dawn automatically.
- Easy installation to lighting fixtures, light poles etc.
- Particularly useful in space limited situations

Max Load:

600W for Max Incandescent Lamps
300W for LED Lamps